


Crimped MIL Connector Sockets for Discrete Wires

XG5N/XG5N-U


Crimped Sockets for Discrete Wires

Join the MIL Connector Series

- XG5N-U Sockets with OMRON's unique lock enable one-hand insertion with a secure lock.
- Save up to 24% of the space required for the XG4A.



Conceptual Application Diagram



Ordering Information



Appearance		Socket and Lock Set Note: The Locks and Sockets are provided separately.		Socket Housing	Lock Levers *1	Crimp Contacts, Type 1	Crimp Contacts, Type 2
No. of contacts	No. of polarity guides	Model		Model	Model	Model	Model
	0	XG5N-100-U	XG5N-100	XG5U-0001		XG5W-0231 (loose contacts)	XG5W-0232 (loose contacts)
10	1	XG5N-101-U	XG5N-101				
14	1	XG5N-141-U	XG5N-141				
16	1	XG5N-161-U	XG5N-161				
20	1	XG5N-201-U	XG5N-201				
26	1	XG5N-261-U	XG5N-261				
30	1	XG5N-301-U	XG5N-301				
34	1	XG5N-341-U	XG5N-341				
40	1	XG5N-401-U	XG5N-401				
50	1	XG5N-501-U	XG5N-501				
	2	XG5N-502-U	XG5N-502			XG5W-0231-R*2 (reel contacts)	XG5W-0232-R*2 (reel contacts)
60	1	XG5N-601-U	XG5N-601				
	2	XG5N-602-U	XG5N-602				
64	1	XG5N-641-U	XG5N-641				
	2	XG5N-642-U	XG5N-642				

*1. Each XG5N-□□□ Connector requires two Lock Levers.

*2. Order the required number of reels (10,000 contacts).

Note: The pitch between the two polarity guides on Connectors with 50, 60, or 64 contacts is 22.86 mm.

■ Mating



■ Ratings and Characteristics

Rated current	3 A/contact (with AWG22 wire) 2 A/contact (with AWG24 wire) 1 A/contact (with AWG26 or AWG28 wire)
Rated voltage	250 VAC
Contact resistance	20 mΩ max. (at 20 mV, 100 mA max.)
Insulation resistance	1,000 MΩ min. (at 500 V DC)
Withstand voltage	500 VAC for 60 s (leakage current: 1 mA max.)
Total insertion force	No. of contacts × 1.96 N max.
Individual pull-out force	0.29 N min.
Insertion durability	50 times
Ambient operating temperature	−55 to 105°C (with no icing)

■ Applicable Contacts and Wires

Applicable Contacts	Applicable wires	
	AWG No. (UL1007 twisted wires)	Conductor construction (elements/element diameter (mm))
XG5W-0231	22	17/0.16
	24	11/0.16
	26	7/0.16
XG5W-0232	24	11/0.16
	26	7/0.16
	28	7/0.127


■ Materials and Finish

Housing		Fiber-glass reinforced PBT resin (UL94 V-2)/black
Lock Levers		POM resin (UL94 HB)/black
Contacts	Mating end	Phosphor bronze/nickel base, gold plated (0.15 μm)
	Crimped section	Phosphor bronze/nickel base, tin plated (2.0 μm)



■ Dimensions

(Unit: mm)

XG5N-U (with Lock Levers Attached)



XG5N



Dimension (mm) No. of contacts	A	B	C	D
10	17.26	10.16	26.80	26.20
14	22.34	15.24	31.88	31.28
16	24.88	17.78	34.42	33.82
20	29.96	22.86	39.50	38.90
26	37.58	30.48	47.12	46.52
30	42.66	35.56	52.20	51.60
34	47.74	40.64	57.28	56.68
40	55.36	48.26	64.90	64.30
50	68.06	60.96	77.60	77.00
60	80.76	73.66	90.30	89.70
64	85.84	78.74	95.38	94.78

Specified Tools

Manual Crimping Tool

XY2B-7007



Model	Minimum ordering quantity (pieces)
XY2B-7007	1

Contact Removal Tool

XY2E-0003



Model	Minimum ordering quantity (pieces)
XY2E-0003	1

Automatic Applicator

Use an Applicator that is manufactured by Japan Automatic Machine Co., Ltd. Contact information is provided below.

Japan:

Japan Automatic Machine Co., Ltd.

TEL 03-3756-1434

China:

Japan Automatic Machine Technology (Huizhou) Ltd.

6-1-B, Songshan Industrial Park, Huizhou Zhongkai Hi-Tech

Industrial Development Zone, Huizhou, Guangdong, China

TEL(86-752)2771-614 FAX(86-752)2771-619

South-eastern Asia:

Japan Automatic Machine Singapore Pte. Ltd.

HB Centre 12 Tannery Road #04-02, Singapore 347722

TEL 65-6545-8140 FAX 65-6545-8141

USA, Europe:

Toyotamco, Ltd.

8370 Burnham Road Suite 200 EL Paso, TX 79907 USA

TEL (915)595-8825 FAX (915)595-8794

	Crimping Machine	Strip Crimper
Crimp Contacts, Type 1	Planned for the near future. *1	SCA-106700 *2
Crimp Contacts, Type 2		

*1. Inquire for details.

*2. This model number is for standard specifications. Inquire for other specifications.

Safety Precautions


Crimping Method

Always use the specified Crimping Tool or Applicator to wire the crimped contacts.

Refer to the instruction sheet that is provided separately for details.

Contact Insertion Method


Confirm the orientation of the crimped contacts and then insert them all the way to the back of the Socket. After insertion, confirm that the lances are securely set in the lance holes on the socket housing.



Contact Replacement Method

To remove contacts that have been incorrectly inserted, always use the XY2E-0003 Contact Removal Tool.


- (1) Insert the end of the Removal Tool into the lance hole in the socket housing and press the lance all the way inside the socket housing.
- (2) While pressing in on the lance, pull out the Contact.
- (3) Insert a new Contact.



Note: Do not use any Contacts that have been removed.

Attaching the Lock Levers

Attach the holes in the Lock Levers to the protrusions on both sides of the housing and make sure that they are set securely.



Precautions for Correct Use

When mating the Sockets with XG4C Box Plugs, always use the XG5U-0001 Lock Levers. Otherwise the Connectors may become disconnected due to vibration or shock.

Storage

- (1) Do not store the Sockets in locations subject to dust or high humidity.
- (2) Do not store the Sockets in locations close to sources of gases such as ammonia gas or sulfide gas.

<https://hoplongtech.com>
HOTLINE: 1900.6536

Note: Do not use this document to operate the Unit.

OMRON Corporation Electronic and Mechanical Components Company
Contact: www.omron.com/ecb

OMRON ELECTRONIC COMPONENTS EUROPE B.V.
Wegalaan 57, 2132 JD Hoofddorp, THE NETHER LANDS
Tel: (31) 23-568-1200/Fax: (31) 23-568-1212

OMRON ELECTRONIC COMPONENTS LLC
55 East Commerce Drive, Suite B, IL 60173 U.S.A.
Tel: (1) 847-882-2288/Fax: (1) 847-882-2192

OMRON ELECTRONIC COMPONENTS PTE LTD.
438A Alexandra Road #05-05/08 Alexandra
Technopark Singapore 119967
Tel: (65) 6376-3200/Fax: (65) 6376-3211

OMRON ELECTRONIC COMPONENTS TRADING (SHANGHAI) LTD. SHANGHAI OFFICE
27F Xin Mei Union Square, 999 Pudong South Road, Pudong New Area, Shanghai, CHINA 200120
Tel: (86) 21-6859-5919/Fax: (86) 21-6859-5911

OMRON ELECTRONIC COMPONENTS CO., LTD.
307, Teheran Office Bldg. #707-38, Yeoksam-dong, Gangnam-gu, Seoul, Korea
Tel: (82) 2-567-5020/Fax: (82) 2-567-5804

Authorized Distributor:

© OMRON Corporation 2012 All Rights Reserved.
In the interest of product improvement, specifications are subject to change without notice.

Cat. No. G023-E1-03

0713(0112) (O)